
Digital Trunk Diagnostic (LD 60)

The DTRK messages indicate problems with Digital Trunks detected by the resident Trunk Diagnostic program.

DTRK messages

DTRK0433	Timeout when waiting for ready to outpulse.
DTRK0434	Timeout when waiting for stop outpulse.
DTRK0435	Failure to receive second half of BUR signal on digital trunks.
DTRK0436	Digits received before seizure acknowledge sent.
DTRK0437	Failure to receive second half of OPCA or OPRC.
DTRK0438	Timeout when waiting for first half of next OPCA or OPRC.
DTRK0439	Timeout when waiting for second half of network call transfer (NXFR) flash.
DTRK0440	Failure to receive second half of WNKS signal (GLARE CONDITION).
DTRK0500	A Forward Release message has been sent on loop/card I channel ch and has not been acknowledged by a Backward Release. Action: Check the configuration of the trunks at both end if the problem occurs regularly. (SICA tables in OVL 73 and FRIN, FRRC, and RLSM in LD 16).
DTRK0501 tn	A WNKS signal of invalid duration has been received.
DTRK0502 tn	An unexpected seize message has been received on a disconnecting trunk.
DTRK0503 loop channel	An unrecognized message subtype in Messin 28 received from DTI2 loop on CDT2 card.

DTRK

- DTRK0504 loop channel DP digits collection report received from CDTI2 trunk which is not defined with CLS DIPP.
- DTRK0505 loop channel A recognized DP digits collection report from CTI2 trunk.
- DTRK0506 loop channel A problem was discovered by CDTI2 FW during DP digits collection.
- DTRK0507 loop channel An unexpected CDTI2 CIS special signalling input received. It is permissible only for CDTI2 loops with CISFW=YES defined in LD73.
- DTRK0508 loop channel An unrecognized CDTI2 CIS special signalling input received.
- DTRK0509 A problem was discovered by CDT12FW during MFS protocol performing.
- DTRK0510 CIS MFS bad transmission threshold exceeded.
- DTRK0511 CIS MFS bad transmission threshold exceeded.